

## NP-Series - Valve Regulated Lead Acid Battery NP2.8-6




SPECIFICATIONS			
Nominal voltage	6	V	
20-hr rate Capacity to 1.75VPC at 20°C	2.8	Ah	
10-hr rate Capacity to 1.75VPC at 20°C	2.5	Ah	
DIMENSIONS	<del>-</del>		
Length	134 (±1)	mm	
Width	34 (±1)	mm	
Height	, ,	mm	
(height over terminals)	64 (±2)	mm	
Mass (typical)	0.57	kg	
TERMINAL TYPE			
FASTON (Quickfit / release)	4.75	mm	
OPERATING TEMPERATURE RANGE			
Storage	-20°C to	o +60°C	
Charge	-15°C to +50°C		
Discharge		-20°C to +60°C	
STORAGE			
Capacity loss per month at 20°C (approx)	3	%	
CASE MATERIAL			
Standard Option	ABS (UI	ABS (UL.94:HB)	
Flame retardant option (FR)	ABS (UL94:V0)		
CHARGE VOLTAGE			
Float charge voltage at 20°C	6.825 (±1%)	V	
loat charge voltage at 20 0	2.275 (±1%)	V/cell	
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C	
Cyclic (or Boost) charge at 20°C	7.26 (±3%) 2.42 (±3%)	V V/cell	
Cyclic Charge voltage temperature correction factor (for variations from the standard 20°C) CHARGE CURRENT	-4	mV/cell/°C	
Float charge current limit	No limit	A	
Cyclic (or Boost) charge current limit	0.7	A	
MAXIMUM DISCHARGE CURRENT	0.7	A	
1 second	84	A	
1 minute	28	A	
	20	A	
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE (according to EN IEC 60896-21)			
Internal resistance	N/A	mΩ	
Short-Circuit current	N/A N/A	MΩ	
Short-Circuit current  IMPEDANCE	IW/A	A	
Measured at 1 kHz	20	mΩ	
	30	11177	
PERFORMANCE & CHARACTERISTICS	1 15		
Refer to the technical manual	NP		
DESIGN LIFE	1		
EUROBAT Classification: Standard Commercial	3 to 5	years	
Yuasa design life @ 20°C	up to 5	years	
SAFETY			
Installation Can be installed and operated in any orientation except permar	nently inverted		
Handles	• • • • • • • • • • • • • • • • • • • •		
Batteries must not be suspended by their handles (where fitted	)		
Vent valves	,		
Each cell is fitted with a low pressure release valve to allow gas	sees to escape and ther	reseal	
Cae Pelease	soos to cocupe and their	1 1030ai.	

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and





## **3RD PARTY CERTIFICATIONS**

ISO 9001 - Quality Management Systems ISO 14001 - Environmental Management Systems EN 18001 - OHSAS Management Systems UNDERWRITERS LABORATORIES Inc.



## **STANDARDS**

IEC61056

LAYOUT







ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.2 / Issue Date: March 2011

מיקום הפריט: סוללות, מצברים ומטענים / סוללות נטענות ומצברים / מצברי עופרת LEAD ACID

6V 2.8AH תיאור הפריט: מצבר עופרת נטען

יצרן: יואסה / YUASA

NP2.8-6 :מק"ט יצרן

יבואן : טלמיר אלקטרוניקה בע"מ



Gas Release

container Recycling

regulations

www.talmir.co.il