

## NP-Series - Valve Regulated Lead Acid Battery NP12-12




SPECIFICATIONS			
Nominal voltage	12	V	
20-hr rate Capacity to 1.75VPC at 20°C	12	Ah	
10-hr rate Capacity to 1.75VPC at 20°C	11.1	Ah	
DIMENSIONS			
Length	151 (±1)	mm	
Width	98 (±1)	mm	
Height	30 (±1)	mm	
(height over terminals)	97.5 (±2)	mm	
Mass (typical)	4.05	kg	
TERMINAL TYPE	4.03	- Ng	
	6.35	mm	
FASTON (Quickfit / release)	0.35	mm	
OPERATING TEMPERATURE RANGE	1		
Storage		-20°C to +60°C	
Charge		-15°C to +50°C	
Discharge	-20°C to	+60°C	
STORAGE			
Capacity loss per month at 20°C (approx)	3	%	
CASE MATERIAL			
Standard Option	ABS (UL	ABS (UL.94:HB)	
Flame retardant option (FR)	ABS (UI	ABS (UL94:V0)	
CHARGE VOLTAGE			
Float charge voltage at 20°C	13.65 (±1%) 2.275 (±1%)	V V/cell	
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C	
Cyclic (or Boost) charge at 20°C	14.5 (±3%) 2.42 (±3%)	V V/cell	
Cyclic Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C	
CHARGE CURRENT			
Float charge current limit	No limit	Α	
Cyclic (or Boost) charge current limit	3	Α	
MAXIMUM DISCHARGE CURRENT			
1 second	360	Α	
1 minute	75	Α	
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE			
(according to EN IEC 60896-21)			
Internal resistance	44.39	mΩ	
Short-Circuit current	320	A	
IMPEDANCE	323	,,	
Measured at 1 kHz	18	mΩ	
PERFORMANCE & CHARACTERISTICS	10	11122	
	ND I		
Refer to the technical manual	NP		
DESIGN LIFE			
EUROBAT Classification: Standard Commercial	3 to 5	years	
Yuasa design life @ 20°C	up to 5	years	
SAFETY			
Installation			
Can be installed and operated in any orientation except pern	nanently inverted		
Handles	•		
Batteries must not be suspended by their handles (where fitt	ed)		
Vent valves	,		
Each cell is fitted with a low pressure release valve to allow	rasses to escane and then	reseal	
	Jacobs to cocape and then	rooca.	

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and





## **3RD PARTY CERTIFICATIONS**

ISO 9001 - Quality Management Systems ISO 14001 - Environmental Management Systems EN 18001 - OHSAS Management Systems UNDERWRITERS LABORATORIES Inc. VdS (Germany) - VdS No: G189170



## **STANDARDS**

IEC61056

LAYOUT









ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.2 / Issue Date: March 2011

מיקום הפריט: סוללות, מצברים ומטענים / סוללות נטענות ומצברים / מצברי עופרת LEAD ACID

12V 12AH תיאור הפריט: מצבר עופרת נטען

יצרן: יואסה / YUASA NP12-12 מק"ט יצרן:

יבואן : טלמיר אלקטרוניקה בע"מ



Gas Release

container Recycling

regulations

www.talmir.co.il