


## NP-Series - Valve Regulated Lead Acid Battery NP24-12I

SPECIFICATIONS			
Nominal voltage	12	V	
20-hr rate Capacity to 1.75VPC at 20°C	24	Ah	
10-hr rate Capacity to 1.75VPC at 20°C	22.3	Ah	
DIMENSIONS			
Length	166 (±1)	mm	
Width	175 (±1)	mm	
Height	125 (±2)	mm	
(height over terminals)	N/A	mm	
Mass (typical)	9	kg	
TERMINAL TYPE		<u> </u>	
Female threaded terminal	M5		
Torque	2.45	Nm	
OPERATING TEMPERATURE RANGE			
Storage	-20°C to	) +60°C	
Charge		-15°C to +50°C	
Discharge		-20°C to +60°C	
STORAGE			
Capacity loss per month at 20°C (approx)	3	%	
CASE MATERIAL			
Standard Option	ABS (UL	ABS (UL.94:HB)	
Flame retardant option (FR)	`	ABS (UL94:V0)	
CHARGE VOLTAGE	- (-	,	
Float charge voltage at 20°C	13.65 (±1%)	V	
	2.275 (±1%)	V/cell	
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C	
,	14.5 (±3%)	V	
Cyclic (or Boost) charge at 20°C	2.42 (±3%)	V/cell	
Cyclic Charge voltage temperature correction factor	-4	mV/cell/°C	
(for variations from the standard 20°C)			
CHARGE CURRENT			
Float charge current limit	No limit	Α	
Cyclic (or Boost) charge current limit	6	Α	
MAXIMUM DISCHARGE CURRENT			
1 second	720	Α	
1 minute	48	Α	
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE			
(according to EN IEC 60896-21)			
Internal resistance	22.19	mΩ	
Short-Circuit current	656	Α	
IMPEDANCE			
Measured at 1 kHz	16	mΩ	
PERFORMANCE & CHARACTERISTICS			
Refer to the technical manual	NP		
DESIGN LIFE			
EUROBAT Classification: Standard Commercial	3 to 5	years	
Yuasa design life @ 20°C	up to 5	years	
SAFETY	ap 10 0	yours	
Installation	an anthri inrranta d		
Can be installed and operated in any orientation except pern	ianemily inverted		







### **3RD PARTY CERTIFICATIONS**

ISO 9001 - Quality Management Systems ISO 14001 - Environmental Management Systems EN 18001 - OHSAS Management Systems UNDERWRITERS LABORATORIES Inc. VdS (Germany) - VdS No: G182026



## **STANDARDS**

IEC61056









ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.2 / Issue Date: March 2011

# Vent valves

Handles

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

#### Gas Release

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed container

### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations

מיקום הפריט: סוללות, מצברים ומטענים / סוללות נטענות ומצברים / מצברי עופרת LEAD ACID

12V 24AH תיאור הפריט: מצבר עופרת נטען

יצרן: יואסה / YUASA NP24-12I מק"ט יצרן:

יבואן: טלמיר אלקטרוניקה בע"מ



www.talmir.co.il

Batteries must not be suspended by their handles (where fitted)