


NP-Series - Valve Regulated Lead Acid Battery NP65-12I

YU	ASA

SPECIFICATIONS			
Nominal voltage	12	V	
20-hr rate Capacity to 1.75VPC at 20°C	65	Ah	
10-hr rate Capacity to 1.75VPC at 20°C	60.5	Ah	
DIMENSIONS	1		
Length	350 (±1)	mm	
Width	166 (±1)	mm	
Height	174 (±2)	mm	
(height over terminals)	N/A	mm	
Mass (typical)	23	kg	
TERMINAL TYPE		<u> </u>	
Female threaded terminal	M6		
Torque	4.76	Nm	
OPERATING TEMPERATURE RANGE	1.70	14	
Storage	-30°C to	1460°C	
		-20°C to +60°C -15°C to +50°C	
Charge Discharge	-15°C to		
STORAGE	-20 0 10	7 +00 0	
Capacity loss per month at 20°C (approx)	3	%	
CASE MATERIAL	<u> </u>	/6	
Standard Option	APC // III	0.4:HB)	
		ABS (UL.94:HB)	
Flame retardant option (FR)	ABS (U	L94:V0)	
CHARGE VOLTAGE	10.05 (.40/)	V	
Float charge voltage at 20°C	13.65 (±1%) 2.275 (±1%)	V V/cell	
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C	
Cyclic (or Boost) charge at 20°C	14.5 (±3%) 2.42 (±3%)	V V/cell	
Cyclic Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C	
CHARGE CURRENT			
Float charge current limit	No limit	A	
Cyclic (or Boost) charge current limit	16.25	A	
MAXIMUM DISCHARGE CURRENT	10.23	A	
1 second	1950	A	
1 minute	48	A	
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE			
(according to EN IEC 60896-21)			
Internal resistance	10.51	mΩ	
Short-Circuit current	1375	Α	
IMPEDANCE			
Measured at 1 kHz	12	mΩ	
PERFORMANCE & CHARACTERISTICS			
Refer to the technical manual	NP		
DESIGN LIFE			
EUROBAT Classification: Standard Commercial	3 to 5	years	
Yuasa design life @ 20°C	up to 5	years	
SAFETY			
Installation			
Can be installed and operated in any orientation except perr	nanently inverted		
Handles			





3RD PARTY CERTIFICATIONS

ISO 9001 - Quality Management Systems ISO 14001 - Environmental Management Systems EN 18001 - OHSAS Management Systems UNDERWRITERS LABORATORIES Inc. VdS (Germany) - VdS No: G183008



STANDARDS

IEC61056

LAYOUT









ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE

Issue No.: V.2 / Issue Date: Mar 2011

Batteries must not be suspended by their handles (where fitted)

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

Gas Release

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed container

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations

מיקום הפריט: סוללות, מצברים ומטענים / סוללות נטענות ומצברים / מצברי עופרת LEAD ACID

12V 65AH תיאור הפריט: מצבר עופרת נטען

יצרן: יואסה / YUASA NP65-12I מק"ט יצרן:

יבואן: טלמיר אלקטרוניקה בע"מ



www.talmir.co.il