


NP-Series - Valve Regulated Lead Acid Battery NP3.2-12



SPECIFICATIONS		
Nominal voltage	12	V
20-hr rate Capacity to 1.75VPC at 20°C	3.2	Ah
	2.9	
10-hr rate Capacity to 1.75VPC at 20°C	2.9	Ah
DIMENSIONS	1 12111	
Length	134 (±1)	mm
Width	67 (±1)	mm
Height	24 (8)	mm
(height over terminals)	64 (±2)	mm
Mass (typical)	1.2	kg
TERMINAL TYPE	<u> </u>	
FASTON (Quickfit / release)	4.75	mm
OPERATING TEMPERATURE RANGE		
Storage	-20°C to +60°C	
Charge	-15°C to +50°C	
Discharge	-20°C to +60°C	
STORAGE		
Capacity loss per month at 20°C (approx)	3	%
CASE MATERIAL		
Standard Option	ABS (UL.94:HB)	
Flame retardant option (FR)	ABS (UL94:V0)	
CHARGE VOLTAGE		
Float charge voltage at 20°C	13.65 (±1%)	V
riout charge voltage at 20 0	2.275 (±1%)	V/cell
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C
Cyclic (or Boost) charge at 20°C	14.5 (±3%) 2.42 (±3%)	V V/cell
Cyclic Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C
CHARGE CURRENT	<u> </u>	
Float charge current limit	No limit	A
Cyclic (or Boost) charge current limit	0.8	Α
MAXIMUM DISCHARGE CURRENT		
1 second	96	Α
1 minute	32	Α
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE		
(according to EN IEC 60896-21)		
Internal resistance	N/A	mΩ
Short-Circuit current	N/A	A
IMPEDANCE		
Measured at 1 kHz	50	mΩ
PERFORMANCE & CHARACTERISTICS		
	ND I	
Refer to the technical manual DESIGN LIFE	NP	
	1 0 1	
EUROBAT Classification: Standard Commercial	3 to 5	years
Yuasa design life @ 20°C	up to 5	years
SAFETY		
Installation		
Can be installed and operated in any orientation except perma	nently inverted	
Handles	-	
Batteries must not be suspended by their handles (where fitted)	
Vent valves	,	
Each cell is fitted with a low pressure release valve to allow ga	sses to escane and then	reseal
2.5. 25	cood to coodpe and then	





3RD PARTY CERTIFICATIONS

ISO 9001 - Quality Management Systems ISO 14001 - Environmental Management Systems EN 18001 - OHSAS Management Systems UNDERWRITERS LABORATORIES Inc.



STANDARDS

IEC61056

LAYOUT







ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.2 / Issue Date: March 2011

container Recycling

Gas Release

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed

מיקום הפריט: סוללות, מצברים ומטענים / סוללות נטענות ומצברים / מצברי עופרת LEAD ACID

12V 3.2AH תיאור הפריט: מצבר עופרת נטען

יצרן: יואסה / YUASA NP3.2-12 :מק"ט יצרן

יבואן : טלמיר אלקטרוניקה בע"מ



www.talmir.co.il