

Palm Size Digital Multimeter

TENMA™



Description

The new generation Palm Size Multimeters redefines the performance standards for entry-level digital multimeters. These models ensures that users can work safely in CAT II 250V environment.

Features

Clear LCD Display
Equipped with Comfortable Protective Cover, Test Probe Holder
2 Meters Drop Test, Precision Protection
Auto Power Off
Auto Backlight Off
Loud Buzzer Sound
Knobs Shift Smoothly, In-line with Ergonomics

Specification Table

| Characteristics | 72-13430 | 72-13435 | 72-13440 |
|------------------------|--|--|--|
| Max Display | | 1999 | |
| Range Selection | Auto | Manual | |
| Diode Test | | ✓ | |
| Continuity Buzzer | | ✓ | |
| Overload Alarm | | ✓ | |
| Data Hold | | ✓ | |
| Relative Mode | ✓ | - | |
| Low Battery Indication | | ✓ | |
| NCV | - | - | ✓ |
| DC Voltage | 200mV/2V/20V/200V/250V, ±(0.8%+1) | 200mV/2000mV/20V/200V/250V, ±(0.5%+2) | 200mV/2000mV/20V/200V/250V, ±(0.5%+2) |
| AC Voltage | 200mV/2V/20V/200V/250V, ±(1%+2) | 200V/250V, ±(1.2%+3) | 200V/250V, ±(1.2%+10) |
| AC Current | 200µA/2000µA/20mA/ 200mA/2A/10A, ±(1.2%+3) | - | - |
| DC Current | 200µA/2000µA/20mA/ 200mA/2A/10A, ±(1%+3) | 2000µA/20mA/ 200mA/10A, ±(1%+3) | 2000µA/20mA/ 200mA/10A, ±(1%+3) |
| Capacitance | 2nF/20nF/200nF/2uF/ 20uF/200uF, ±(3%+5) | - | - |