



## LC CST Strippers

Our LC CST line of coaxial cable strippers combines high-performance and ergonomic design at an affordable price. Easily remove the outer jacket, shield braid and inner dielectric in a single step.

- Self-regulating tension
- Adjust cutting depth on each blade for varying cable thicknesses with the included hex key
- Pre-set for common strip lengths
- Blades adjust for strip dimensions other than our standard pre-set units\*
- One-year warranty

Technical	Weight	Length
LC CST strippers	1.7 oz. (49 g)	4.25" (108 mm <sup>2</sup> )

  

Ordering	Part No.	Preset Strip Lengths*	Strip Types	Cable Usage
LC CST-58/59	1255	0.315" outer jacket, 0.157" inner dielectric	2- & 3-level, adjustable	RG58, RG59, RG62 AU & RG6
LC CST-11	1256	0.315" outer jacket, 0.157" inner dielectric	2- & 3-level, adjustable	RG8, RG11 & RG213
LC CST CATV "F"	1257	0.236" outer jacket	2-level	RG59, RG6 & RG6 QUAD CATV "F" (preset for RG6 CATV "F")
LC CST-Mini	1258	0.344" outer jacket, 0.094" inner dielectric	2- & 3-level, adjustable	RG178, RG179, RG188, AT&T 735(A), NT735, Belden 1855A, Belden 8218, RG180, RG187, RG188A, RG405 and more
Replacement blade	2263	–	–	–

\* To adjust strip lengths simply change blade locations in the lower jaw to attain the following: .157" (4 mm), .236" (6 mm), .315" (8 mm), .394" (10 mm) and .472" (12 mm)

Not recommended for use on LMR or Teflon cables.

