

Non-Contact AC Voltage Detector





Features

- High power rear flashlight
- Thinner probe tip for working with wall outlets
- Green LED means power on, flashing red LED with beeper means voltage detected
- Low battery self test & Auto power off
- Two modes, green means high voltage mode, yellow means low voltage mode
- Forward facing flashlight
- Flash and Beep rate increase as the detector gets closer to the voltage source helping the user pinpoint live circuits
- Power ON/OFF switch & Silent Mode
- Pocket clip for easy storage
- CATIV 1000V, IP67 Water proof and 2m drop-proof
- ATEX certificate

Specifications

Detection Voltage Range : High Voltage Mode: 100V AC to 1000V AC

sales@talmir.co.il דוא"ל:

Low Voltage Mode: 12V AC to 1000V AC

Frequency Range : 50Hz / 60Hz

Batteries : Two AAA 1.5V batteries

Operating Temperature : 0°C to +50°C (32°F to 122°F) Storage Temperature : -10°C to +60°C (14°F to 140°F)

Humidity : 80% max. Altitude : 2000 meters

Pollution Degree : 2

Safety Compliance : CAT IV - 1000V Warranty : 12 Months

Part Number Table

Description	Part Number
Non-Contact AC Voltage Detector	MP780053



