

Bench Top Digital Multimeter

TENMA™



Special Functions

Basic Functions	Range	Best Accuracy
Display Count		19999
Manual Range		✓
Diode		✓
Transistor		✓
Continuity Buzzer		✓
Low Battery Indication		✓
Data Hold		✓
LCD Backlight		✓
Input Impedance for DCV	Around 10MΩ	✓
Misuse Alarm		✓

Specifications

Basic Functions	Range	Best Accuracy
DC Voltage (V)	200mV/2V/20V/200V/1000V	±(0.1%+3)
AC Voltage (V)	2V/20V/200V/1000V	±(0.5%+20)
DC Current (A)	200μA/2mA/20mA/200mA/10A	±(0.5%+20)
AC Current (A)	2mA/20mA/200mA/10A	±(0.8%+40)
Resistance (Ω)	200Ω/2kΩ/20kΩ/200kΩ/2MΩ/200MΩ	±(0.5%+10)
Capacitance (F)	20nF/2μF/200μF	±(4%+10)
Frequency (Hz)	2kHz/200kHz	±(1.2%+10)
Temperature (°C)	-40°C to +1000°C	±(1.2%+25)

TENMA™

Bench Top Digital Multimeter



General Characteristics

Power	: 220V AC 50Hz Power Adapter or 1.5V Batteries (R14)×6
LCD Size	: 108mm × 34.5mm
Product Colour	: Orange and Grey
Product Net Weight	: 1.5 Kg
Product Size (W×H×D)	: 245mm × 105mm × 300mm
Standard Accessories	: Battery, Test Lead, Alligator Clip, Point Contact Temperature Probe, Multi-Purpose Socket, 220V AC 50Hz Power Adapter (UK/EU)
Standard Warranty	: 12 Months

Part Number Table

Description	Part Number
Bench Top Digital Multimeter	72-14630

